

HP Model	Beginning Serial No	Ending Serial No	Contact Set	Condenser	Tune-Up Kit	Coil	Switch Box
2.5	A855097	& UP	—	—	—	18-5182	18-5793
3	A855097	G710612	—	—	—	18-5182	18-5793
3.3	D901217	& UP	—	—	—	18-5182	18-5793
3.5	⑤ 358136	6202172	18-5153	18-5207	—	18-5178	N/A
3.9	1655013	2498155	18-5140	18-5212	18-5008	—	N/A
4	2498136	2693114	18-5140	18-5212	18-5008	—	N/A
4	⑧ 2771622	A855096	18-5139	—	—	—	N/A
4 (2 cyl.prod. of USA)	5589202	5595531	—	—	—	—	18-5788
4	A855097	G710612	—	—	—	18-5185	—
4	G710613	& UP	—	—	—	—	18-5792
4.5	4107220	& UP	18-5139	—	—	—	N/A
5	⑤ 338136	A855097	18-5153	18-5207	—	18-5178	N/A
5	⑦ 338136	A855097	—	—	—	—	N/A
5	A855097	G710612	—	—	—	18-5185	—
5	G710613	& UP	—	—	—	—	18-5792
5.9 (Mark 6) (Phelon)	888005	1134535	—	—	—	18-5178	—
6	⑤ 888005	1408610	18-5153	18-5206	18-5007	18-5178	N/A
6	1408611	1610264	18-5153	18-5206	18-5007	18-5178	N/A
6	1610265	2529894	18-5140	18-5212	18-5008	—	N/A
6	A197112	& UP	N/A	N/A	N/A	18-5186 ①	18-5777
7.5	⑤ 214324	564117	18-5153	18-5207	—	18-5178	N/A
7.5	2529875	2721150	18-5140	18-5212	18-5008	—	N/A
7.5	3274633	3801457	18-5139	—	—	—	N/A
7.5	5206550	& UP	—	—	—	—	18-5789
8	A197112	& UP	N/A	N/A	N/A	18-5186 ①	18-5777
9.8	1470349	1865778	18-5153	18-5206	18-5007	18-5178	N/A
9.8	1865779A	2708898	18-5140	18-5212	18-5008	—	N/A
9.8	2798057	3795657	18-5139	—	—	—	N/A
9.8	5206550	& UP	—	—	—	—	18-5789
210CC Sail Power	A918999	& UP	N/A	N/A	N/A	18-5186 ①	18-5777
9.9	A197112	& UP	N/A	N/A	N/A	18-5186 ①	18-5777
10	258221	1057993	18-5153	18-5207	—	—	N/A
10	1057994	1122327	18-5153	18-5206	18-5007	18-5178	N/A
10	1290910	1499331	18-5153	18-5206	18-5007	18-5178	N/A
15	1200114	1499331	18-5153	18-5206	18-5007	18-5178	N/A
15	B292414	& UP	N/A	N/A	N/A	18-5186 ①	18-5777
18	5705532	5837436	N/A	N/A	N/A	18-5186 ①	⑨
18	5837437	6443972	N/A	N/A	N/A	18-5186 ①	18-5776
18	6443973	B238463	N/A	N/A	N/A	18-5186 ①	⑨
20	860979	1592567	18-5153	18-5206	18-5007	18-5178	N/A
20	2827677	3537530	18-5139	—	—	—	N/A
20	3537531	4709592	N/A	N/A	N/A	—	18-5786
20	6443973	B238463	N/A	N/A	N/A	18-5186 ①	⑨
20	B238464	G760299	N/A	N/A	N/A	18-5186 ①	18-5777
22	1158546	1499331	18-5153	18-5206	18-5007	18-5178	N/A
25	377150	379008	18-5148	18-5169	18-5012	—	N/A
25	1467499	1499331	18-5153	18-5206	18-5007	18-5178	N/A
25	5705532	6443972	N/A	N/A	N/A	18-5186 ①	18-5776
25	6443973	B238463	N/A	N/A	N/A	18-5186 ①	⑨
25	B238464	G760299	N/A	N/A	N/A	18-5186 ①	18-5777
25	B238464	G760299	N/A	N/A	N/A	18-5186 ①	18-5777
25 4-stroke	G590000	T178499	—	—	—	—	—
30	950250	1260724	18-5148	18-5169	18-5012	—	N/A
30	1271884	1448139	—	18-5169	—	—	N/A
30 Jet	C159200	G589999	—	—	—	18-5186 ①	—
35	1217222	1271337	18-5148	18-5169	18-5012	—	N/A
35	1356948	1448139	—	18-5169	—	—	N/A
35	1571114	2874703	18-5140	18-5212	18-5008	—	N/A
35	6445653	B110788	N/A	N/A	N/A	18-5186 ①	⑩
35	B110789	& UP	N/A	N/A	N/A	18-5186 ①	18-5778
40	831021	1279684	18-5148	18-5169	18-5012	—	N/A
40	1279685	1476509	—	18-5169	—	—	N/A
40 (2 cyl.)	3859435	5823917	N/A	N/A	N/A	—	18-5787
40 (2 cyl.)	5823918	& UP	N/A	N/A	N/A	18-5186 ①	18-5776
40 (4 cyl.)	C159200	G589999	N/A	N/A	N/A	18-5186 ③	18-5881
40 4-stroke	G231123	G760299	N/A	N/A	N/A	18-5180	—

① Two Required ② Three Required ③ Four Required ④ Six Required ⑤ Phelon Magneto only ⑥ Manual start only
 ⑦ Bendix Scintilla Magneto Only ⑧ Except "Gnat"
 ⑨ For Switch Box with Standard Nut Connections Uses 18-5776 –For Switch Box with Bullet Connections Uses 18-5777
 ⑩ For Switch Box with Standard Nut Connections Uses 18-5776 –For Switch Box with Bullet Connections Uses 18-5778

HP Model	Beginning Serial No	Ending Serial No	Contact Set	Condenser	Tune-Up Kit	Coil	Switch Box
45	1139538	1476509	18-5148	18-5169	18-5012	—	N/A
45	1476510	1531958	—	18-5169	—	—	N/A
45/50 (4 cyl.)	5531630	& UP	N/A	N/A	N/A	18-5186 ③	18-5881
45 4-stroke	G231123	T178499	N/A	N/A	N/A	18-5180	—
45 jet	G290585	G589999	N/A	N/A	N/A	18-5791	—
50	1421113	1755548	—	18-5169	—	—	N/A
50	1770179	2116317	—	18-5169	—	—	N/A
50 ⑥	2116318	2305100	—	18-5169	—	—	N/A
50	2305101	2858813	—	—	—	—	18-5779
50 4-stroke & Bigfoot	G231123	T178499	N/A	N/A	N/A	18-5180	—
50/60 (3 cyl.)	6428681	D000749	N/A	N/A	N/A	18-5186 ②	18-5775
50/55/60 (3 cyl.)	D000750	G589999	N/A	N/A	N/A	18-5186 ②	18-5791
65	1542745	2119748	—	18-5169	—	—	N/A
65 ⑥	2119749	2309310	—	18-5169	—	—	N/A
65 jet	D283222	G437999	N/A	N/A	N/A	18-5790	—
65	2309311	2803561	—	—	—	—	18-5779
65	4382057	4571651	N/A	N/A	N/A	—	18-5775
Merc 70	4571652	5128279	N/A	N/A	N/A	—	18-5775
Mariner70	5128280	& UP	N/A	N/A	N/A	18-5186 ②	18-5775
70	1296411	1566239	—	—	—	18-5433 ①	N/A
70	5579016	6428680	N/A	N/A	N/A	18-5186 ②	18-5775
70/75 (3 cyl.)	C272000	D283221	N/A	N/A	N/A	18-5186 ②	18-5775
75 (3 cyl.)	D283222	G437999	N/A	N/A	N/A	—	18-5790
75 (4 cyl.)	6432901	& UP	N/A	N/A	N/A	18-5186 ③	18-5881
80	1335465	1566239	—	—	—	18-5433 ①	N/A
Mariner 80 (4cyl.)	5144547	& UP	N/A	N/A	N/A	18-5186 ③	—
Merc 80 (4cyl.)	5582562	6432900	N/A	N/A	N/A	18-5186 ③	—
80	2559001	3493912	—	—	—	—	18-5779
80 (4 cyl.)	4831999	5141096	—	—	—	—	18-5881
80 (4 cyl.)	5141097	6432900	—	—	—	18-5186	18-5881
80 (3 cyl.)	A996142	C221999	N/A	N/A	N/A	18-5186 ②	18-5775
80 Jet	D283222	G437999	—	—	—	—	18-5881
85	1460999	1766823	—	—	—	18-5433 ①	N/A
85	3493913	4366801	—	—	—	—	18-5779
85 (4 cyl.)	4366802	4831998	—	—	—	—	18-5881
90	1766824	1869775	—	—	—	18-5433 ①	N/A
90	4845301	5299505	—	—	—	—	18-5779
90 (6 cyl.)	5299506	& UP	N/A	N/A	N/A	18-5186 ④	18-5775 ①
90 (3 cyl.)	A996142	D283221	N/A	N/A	N/A	18-5186 ②	18-5775
90 (3 cyl.)	D283222	G437999	—	—	—	18-5186	18-5790
90 Sport Jet (Powerhead)	E023150	E095087	—	—	—	—	18-5775
95	1869776	1935100	—	—	—	18-5433 ①	N/A
95	1935101	2318585	—	—	—	—	18-5779
100 (6 cyl.)	1464949	2318585	—	—	—	18-5433 ①	N/A
100 (4 cyl.)	B209468	6437999	N/A	N/A	N/A	18-5186 ③	18-5881
100 SS	2318586	2836018	—	—	—	—	18-5779
105 Jet	D082000	G303045	—	—	—	18-5186 ④	18-5775 ①
110	1870204	2314955	—	—	—	18-5433 ①	N/A
110	1937325	2314955	—	—	—	—	18-5779
115 (6 cyl.)	5314656	& UP	N/A	N/A	N/A	18-5186 ④	18-5775 ①
115 (6 cyl.)	2836019	5314655	—	—	—	—	18-5779
115 (4 cyl.)	B209468	6437999	N/A	N/A	N/A	18-5186 ③	—
115 (4 cyl.)	C100000	G437999	—	—	—	—	18-5881
125 (4 cyl.)	D283222	G437999	—	—	—	18-5186	18-5881
125	2314956	2839368	—	—	—	—	18-5779
135	2839369	3293233	—	—	—	—	18-5779
V-135	A904646	& UP	N/A	N/A	N/A	18-5186 ④	18-5775 ①
140	3293234	3502805	—	—	—	—	18-5779
140	4865678	5327662	—	—	—	—	18-5779
140	5327663	& UP	N/A	N/A	N/A	18-5186 ④	18-5775 ①
140 Jet	D082000	G960499	—	—	—	18-5186 ④	18-5775 ①
150	3502806	4865677	—	—	—	—	18-5779
150 XS	4868648	5327662	—	—	—	—	18-5779
V-150	4868998	5129429	N/A	N/A	N/A	—	18-5775 ①
V-150	5129480	G960499	N/A	N/A	N/A	18-5186 ④	18-5775 ①

① Two Required ② Three Required ③ Four Required ④ Six Required ⑤ Phelon Magneto only ⑥ Manual start only
 ⑦ Bendix Scintilla Magneto Only ⑧ Except "Gnat" N/A Not Applicable
 ⑨ For Switch Box with Standard Nut Connections Uses 18-5776 –For Switch Box with Bullet Connections Uses 18-5777
 ⑩ For Switch Box with Standard Nut Connections Uses 18-5776 –For Switch Box with Bullet Connections Uses 18-5778

HP Model	Beginning Serial No	Ending Serial No	Contact Set	Condenser	Tune-Up Kit	Coil	Switch Box
V-150 XR2	6616991	A904645	N/A	N/A	N/A	18-5186 ④	18-5775 ①
XR4, Magnum II	B242885	D819999	N/A	N/A	N/A	18-5186 ④	18-5775 ①
V-150 XR6	D820000	G960499	N/A	N/A	N/A	18-5186 ④	18-5775 ①
V-175	4301235	5180108	N/A	N/A	N/A	—	18-5775 ①
V-175,EFI, XR1	5180109	G960499	N/A	N/A	N/A	18-5186 ④	18-5775 ①
V-200	4839034	5158928	N/A	N/A	N/A	—	18-5775 ①
V-200, XR1	5158929	G960499	N/A	N/A	N/A	18-5186 ④	18-5775 ①
200 (DFI)	G386496	G589999	N/A	N/A	N/A	18-5183	—
V-220	B117316	& UP	N/A	N/A	N/A	18-5186 ④	18-5775 ①
V-225	5628028	& UP	N/A	N/A	N/A	18-5186 ④	18-5775 ①

- ① Two Required ② Three Required ③ Four Required ④ Six Required ⑤ Phelon Magneto only ⑥ Manual start only
 ⑦ Bendix Scintilla Magneto Only ⑧ Except "Gnat" N/A Not Applicable
 ⑨ For Switch Box with Standard Nut Connections Uses 18-5776 –For Switch Box with Bullet Connections Uses 18-5777
 ⑩ For Switch Box with Standard Nut Connections Uses 18-5776 –For Switch Box with Bullet Connections Uses 18-5778